

**This Page Is Inserted by IFW Operations
and is not a part of the Official Record**

BEST AVAILABLE IMAGES

**Defective images within this document are accurate representation of
The original documents submitted by the applicant.**

Defects in the images may include (but are not limited to):

- **BLACK BORDERS**
- **TEXT CUT OFF AT TOP, BOTTOM OR SIDES**
- **FADED TEXT**
- **ILLEGIBLE TEXT**
- **SKEWED/SLANTED IMAGES**
- **COLORED PHOTOS**
- **BLACK OR VERY BLACK AND WHITE DARK PHOTOS**
- **GRAY SCALE DOCUMENTS**

IMAGES ARE BEST AVAILABLE COPY.

**As rescanning documents *will not* correct images,
please do not report the images to the
Image Problem Mailbox.**

THIS PAGE BLANK (USPTO)




PCT

WORLD INTELLECTUAL PROPERTY ORGANIZATION
International Bureau

INTERNATIONAL APPLICATION PUBLISHED UNDER THE PATENT COOPERATION TREATY (PCT)

(51) International Patent Classification: A61N 1/30		A1	(11) International Publication Number: WO 97/07854
		(43) International Publication Date: 6 March 1997 (06.03.97)	
(21) International Application Number: PCT/US96/14022		(81) Designated States: AL, AM, AT, AU, AZ, BB, BG, BR, BY, CA, CH, CN, CZ, DE, DK, EE, ES, FI, GB, GE, HU, IS, JP, KE, KG, KP, KR, KZ, LK, LR, LS, LT, LU, LV, MD, MG, MK, MN, MW, MX, NO, NZ, PL, PT, RO, RU, SD, SE, SG, SI, SK, TJ, TM, TR, TT, UA, UG, US, UZ, VN, ARIPO patent (KE, LS, MW, SD, SZ, UG), Eurasian patent (AM, AZ, BY, KG, KZ, MD, RU, TJ, TM), European patent (AT, BE, CH, DE, DK, ES, FI, FR, GB, GR, IE, IT, LU, MC, NL, PT, SE), OAPI patent (BF, BJ, CF, CG, CI, CM, GA, GN, ML, MR, NE, SN, TD, TG).	
(22) International Filing Date: 28 August 1996 (28.08.96)			
(30) Priority Data: 08/520,521 29 August 1995 (29.08.95) US			
(71) Applicant (for all designated States except US): BECTON DICKINSON AND COMPANY [US/US]; 1 Becton Drive, Franklin Lakes, NJ 07417-1880 (US).			
(72) Inventors; and			
(75) Inventors/Applicants (for US only): FLOWER, Ronald, J. [US/US]; 101 Glenwood Mountain Road, Vernon, NJ 07461 (US). DEVINE, James, M. [US/US]; 519 Chester Drive, Lower Burrell, PA 15068 (US).			
(74) Agents: HOFFMANN, Charles, R. et al.; Hoffmann & Baron, 350 Jericho Turnpike, Jericho, NY 11753 (US).			
		Published With international search report. Before the expiration of the time limit for amending the claims and to be republished in the event of the receipt of amendments.	

(54) Title: IONTOPHORETIC DRUG DELIVERY DEVICE HAVING HIGH-EFFICIENCY DC-TO-DC ENERGY CONVERSION CIRCUIT



(57) Abstract

An iontophoresis system includes a transdermal patch (23) for placement against the skin of a patient and a controller (24, 26) electrically connected to the patch (23). The patch (23) includes an anode and cathode electrode, and holds an electrolyte and a medication. The controller includes a DC-DC converter circuit (24) which generates output voltage that is provided to the anode electrode. The controller also includes an adjustable current regulator circuit (26). The current regulator circuit (26) is coupled to the cathode electrode and is adjustable to provide a desired current flow through the electrodes and the skin of the patient. The DC-DC converter circuit (24) is responsive to the voltage drop across the electrodes and adjusts its output voltage in response to this voltage drop and changes in the impedance of the patient's skin.

FOR THE PURPOSES OF INFORMATION ONLY

Codes used to identify States party to the PCT on the front pages of pamphlets publishing international applications under the PCT.

AM	Armenia	GB	United Kingdom	MW	Malawi
AT	Austria	GE	Georgia	MX	Mexico
AU	Australia	GN	Guinea	NE	Niger
BB	Barbados	GR	Greece	NL	Netherlands
BE	Belgium	HU	Hungary	NO	Norway
BF	Burkina Faso	IE	Ireland	NZ	New Zealand
BG	Bulgaria	IT	Italy	PL	Poland
BJ	Benin	JP	Japan	PT	Portugal
BR	Brazil	KE	Kenya	RO	Romania
BY	Belarus	KG	Kyrgyzstan	RU	Russian Federation
CA	Canada	KP	Democratic People's Republic of Korea	SD	Sudan
CF	Central African Republic	KR	Republic of Korea	SE	Sweden
CG	Congo	KZ	Kazakhstan	SG	Singapore
CH	Switzerland	LI	Liechtenstein	SI	Slovenia
CI	Côte d'Ivoire	LK	Sri Lanka	SK	Slovakia
CM	Cameroon	LR	Liberia	SN	Senegal
CN	China	LT	Lithuania	SZ	Swaziland
CS	Czechoslovakia	LU	Luxembourg	TD	Chad
CZ	Czech Republic	LV	Latvia	TG	Togo
DE	Germany	MC	Monaco	TJ	Tajikistan
DK	Denmark	MD	Republic of Moldova	TT	Trinidad and Tobago
EE	Estonia	MG	Madagascar	UA	Ukraine
ES	Spain	ML	Mali	UG	Uganda
FI	Finland	MN	Mongolia	US	United States of America
FR	France	MR	Mauritania	UZ	Uzbekistan
GA	Gabon			VN	Viet Nam

IONTOPHORETIC DRUG DELIVERY DEVICE HAVING
HIGH-EFFICIENCY DC-TO-DC ENERGY CONVERSION CIRCUIT

BACKGROUND OF THE INVENTION

Field of the Invention

5 The present invention generally relates to
iontophoretic drug delivery devices, and more
particularly relates to electronic circuits for use in
iontophoretic drug delivery devices which deliver a
controlled voltage or current to a patient receiving
10 medication transdermally.

Description of the Prior Art

15 Iontophoresis may be defined as the electrically
driven application of drugs or medications, in their
ionic form, to the surface tissues of a patient. The
application of electric current causes the migration of
ions into the tissue, where such migration is
proportional to the quantity of current applied through
the iontophoretic system.

20 A basis iontophoretic device includes a controller
and a drug delivery device, commonly called a transdermal
patch. The controller may include a power source and a
circuit to control the application of voltage or current
from the power source to the patch. The patch generally
includes two or more electrodes, the ionic medication and
25 an electrolyte. When the patch is placed against the
skin of the patient and a voltage is impressed across the
electrodes, a circuit through the patient's skin is
created and current flows through the skin of the
patient, driving the ionic medication into the skin and
30 tissue to be absorbed by the patient's body.

 In some applications, it may be desirable to
increase the voltage provided to the patch electrodes

from the power source. This is especially true when the iontophoretic device is battery powered, and it may be necessary to increase a relatively low battery voltage to a higher, but safe, electrode voltage to more effectively drive the ionic medication into the skin and tissue of the patient. In such applications, a boost circuit or step-up DC-DC converter may be suitable for use, such as shown in Figure 4 of U.S. Patent No. 5,306,235.

OBJECTS AND SUMMARY OF THE INVENTION

It is an object of the present invention to provide an improved circuit design for an iontophoretic drug delivery device.

It is another object of the present invention to provide a high efficiency DC-DC converter circuit for use in an iontophoresis system.

It is a further object of the present invention to provide a self-regulating DC-DC converter circuit for an iontophoresis system which adjusts to changes in the impedance of the tissue of a patient undergoing iontophoresis.

It is yet a further object of the present invention to provide a DC-DC converter circuit which adjusts its output voltage in response to a desired drug delivery current or to variations in the impedance of a patient undergoing iontophoresis.

It is yet another object of the present invention to provide a DC-DC converter circuit which is at least partially failsafe to prevent undesired current flow to a patient undergoing iontophoresis.

In accordance with one form of the present invention, an iontophoresis system includes an iontophoretic drug delivery device, commonly called a patch, for placement against the skin of a patient, and a controller electrically connected to the patch and having circuitry for controlling current and voltage provided to the patch. More specifically, the patch includes at least a first electrode, which may act as an anode, and at least a second electrode, which may act as a cathode. The patch also includes containers or other structure for holding an electrolyte and a medication. The electrolyte and medication are situated on the patch such that they are in electrical communication with one or the other of the first and second electrodes.

The controller of the iontophoresis system includes a DC-DC converter circuit. The DC-DC converter circuit generates an output voltage which is provided to at least one of the first and second electrodes.

The controller also includes an adjustable current regulator circuit. The current regulator circuit is coupled to the other electrode and is adjustable to provide a desired current flow through the first and second electrodes and the skin of the patient when the patch is placed on the patient's skin.

The DC-DC converter circuit is responsive to the voltage drop across the first and second electrodes. The circuit adjusts its output voltage in response to this voltage drop to provide just the voltage needed across the electrodes and adjustable current regulator for safe and effective drug delivery to the patient without the wasteful consumption of power. The controller circuitry, which includes both the DC-DC converter circuit and the adjustable current regulator circuit, is also particularly responsive to any sudden changes in current

or voltage provided to the patch, such as if the patient's skin impedance suddenly changed or the current regulator circuit is adjusted to provide a different drug delivery current to the patient during the iontophoretic process.

These and other objects, features and advantages of the present invention will become apparent from the following detailed description of illustrative embodiments thereof, which is to be read in connection with the accompanying drawings.

BRIEF DESCRIPTION OF THE DRAWINGS

Figure 1 is a block diagram of an iontophoresis system formed in accordance with the present invention, with portions thereof shown in cross-section.

Figure 2 is a block diagram of a circuit of the iontophoresis system formed in accordance with the present invention.

Figure 3 is a detailed schematic diagram of the circuit shown in Figure 2 of the iontophoresis system formed in accordance with the present invention.

DETAILED DESCRIPTION OF THE PREFERRED EMBODIMENTS

Referring initially to Figure 1 of the drawings, it will be seen that an iontophoresis system for delivering medication to a patient transdermally, that is, through the skin of the patient, basically includes a transdermal drug delivery device, commonly referred to as a patch 2, for placement against the skin of a patient, and a controller 4 which is electrically coupled to the patch 2.

One form of a transdermal drug delivery device (i.e., the patch 2) is illustrated by Figure 1. The transdermal patch basically includes a first electrode 6, which may act as an anode, and a second electrode 8, which may act as a cathode. The patch is placeable against the skin 10 of a patient so that the anode electrode 6 and cathode electrode 8 are in electrical communication with the patient's skin.

Adjacent to the anode (i.e., the first electrode 6) is a container 12 or other suitable structure defining a well for holding a medication 14 in place between the anode 6 and the skin 10 of the patient. Similarly, adjacent to the cathode (i.e., the second electrode 8) is a container 16 or other suitable structure forming a well for holding an electrolyte 18 in place between the cathode 8 and the skin 10 of the patient.

When a voltage V_a is impressed across the first and second electrodes 6, 8, current I_a will flow through the skin 10 of the patient, driving the medication 14, which may be ionic, into the skin and tissue to be absorbed by the patient's body. To simplify the explanation, only two electrodes are shown in Figure 1. However, it should be understood that the anode and cathode may be segmented, or multiple electrodes may be provided, as is well known in the art.

Referring again to Figure 1 of the drawings, the controller 4 of the iontophoresis system includes a current and voltage delivery circuit 20 which controls the current passing through each of the electrodes 6, 8 and the voltage across the electrodes. The controller may also include a power source 22, such as a battery, which is connected to the current and voltage delivery circuit 20. The controller circuit 20 is connected to the transdermal patch 2 to provide a controlled current

and voltage to the electrodes and thus the skin of the patient. As will become evident, the controller circuit 20 is advantageously designed with the capability of providing an adjustable but regulated drug delivery current and just the right voltage across the electrodes for proper drug delivery, and with the ability to react to sudden changes in voltage or current requirements due, for example, to changes in the patient's skin impedance or changes in the impedance of the transdermal patch.

Figure 2 illustrates in block diagram form one form of the controller circuit used in the present invention. The power source or battery 22 is designated as voltage V1. The load impedance Z represents the impedance of the patch/patient circuit 23. More specifically, impedance Z includes the impedance of the transdermal patch 2, such as the impedance of the electrodes 6,8, the medication 14 and electrolyte 18 and the impedance of the connection between the transdermal patch and the patient, as well as the impedance of the patient's skin 10.

As shown in Figure 2, the controller circuit 20 includes a DC-DC converter circuit 24. The DC-DC converter circuit is connected to the power source (represented by voltage V1) and generates an output voltage V2 which is provided between ground and at least one of the electrodes, such as the anode 6, of the transdermal patch. The DC-DC converter 24 may be a step-up converter which effectively increases the voltage V1 of the power source and generates an output voltage V2. Such a step-up converter would be useful in a portable iontophoresis system which is battery powered and which is worn by the patient during an iontophoretic session.

Alternatively, it is envisioned that the DC-DC converter 24 may provide an output voltage V2 which is equal to the power source voltage V1, in order to isolate

the patient directly from the power source, or may even be a step-down converter, providing an output voltage V2 which is less than the voltage V1 of the power source. In any event, it is preferred if the DC-DC converter 24 is adjustable so that it may vary the output voltage V2 in response to a control signal (such as a fed back voltage level) provided to it. A preferred form of a DC-DC converter will be described in relation to Figure 3.

As shown in Figure 2, the controller circuit 20 also includes an adjustable current regulator circuit 26. The adjustable current regulator circuit 26 is coupled to the other electrode, such as the cathode 8, of the transdermal patch 2, and is adjustable to provide a desired current flow through the first and second electrodes and the skin 10 of the patient undergoing iontophoresis. The current regulator circuit 26 may be a series pass regulator, for example, and may be controlled by a voltage Vr on an input of the circuit. By adjusting voltage Vr, the current regulator circuit will source or sink a desired drug delivery current flowing through the patch electrodes 6,8 and skin 10 of the patient.

The voltage on the second electrode, or cathode 8, may be fed back to the DC-DC converter circuit 24 through a buffer amplifier 28 or the like so that the DC-DC converter circuit will be responsive to the voltage drop across the current regulator 26 and, indirectly, across the first and second electrodes 6,8. The DC-DC converter circuit 24 is designed to provide just the necessary voltage across the electrodes and current regulator for proper drug delivery and in order to minimize power consumption, and it does this in response to the voltage provided to it from the cathode 8.

The controller circuit 20 of the present invention shown in Figure 2 operates in the following manner. A

voltage V_r is selected and applied to the current regulator circuit 26 which will cause a corresponding desired drug delivery current to flow through the electrodes 6,8 of the transdermal patch 2 and through the patient's skin 10 when the patch is placed on the patient. The patient and patch together will have a particular impedance Z , which may vary as will be further explained.

For example, if the impedance of the patch and patient together is 15,000 ohms, and the desired drug delivery current flowing through the patch and patient is set for 2 milliamperes, then by Ohm's law, there will be a voltage drop V_p across the patch/patient circuit 23 of 30 volts. These would be, as an example, the expected impedance and desired drug delivery current flow during the iontophoresis session for a particular medication being applied transdermally. Under these circumstances, the DC-DC converter 24 will be initially configured to step-up the battery voltage V_1 to a safe but more useful output voltage V_2 which is applied to one of the electrodes 6,8 of the patch to provide the necessary voltage across the patch/patient circuit 23 and the current regulator 26 and thus ensure that the necessary at least 30 volts is available across the patch and that the desired current flow of 2 milliamperes is not limited to a lower value.

The DC-DC converter 24 is designed so that there will be only a minimal voltage drop V_s across the adjustable current regulator circuit. In other words, the output voltage V_2 of the DC-DC converter 24 is equal to the sum of voltage V_p and voltage V_s , since the patch/patient circuit 23 is in series with the current regulator circuit 26 and voltage V_2 is provided across the series connection of the current regulator circuit 26 and patch/patient circuit 23. The voltage at the cathode

8 of the transdermal patch 2 is applied through the buffer amplifier 28 to the voltage control input of the DC-DC converter 24 so that the iontophoresis system is stable and providing a safe, regulated voltage at the desired drug delivery current with minimal wasteful voltage drop across the current regulator circuit 26.

However, it is known that the impedance of a patient's skin can range from over 100,000 ohms to nearly 1,000 ohms, depending on the duration that the iontophoretic current is applied, the magnitude of the current which is being delivered, the location of the system on the patient's body, and other factors. In a system where the desired current level, which is determined in part by the drug administered to the patient, is 2 milliamperes, a voltage potential of 100 volts would result if the skin impedance is 50,000 ohms. Such a voltage would cause undesirable sensations to the user and may result in skin irritation or burns. The system of the present invention is self-regulating to ensure that this will not occur and at the same time providing the minimum voltage necessary for drug delivery.

If, for example, the impedance of the patient (and patch) were not the expected 15,000 ohms in the example given above but rather was 50,000 ohms, which is more likely to happen at the start of iontophoresis, then the voltage drop V_p across the patch/patient circuit 23 would be 100 volts at the desired current of 2 milliamperes. To prevent this, the DC-DC converter 24 is preferably self-limiting to provide a pre-selected maximum voltage, such as 30 volts, to the patch. By Ohm's law, the current flowing through the patient's skin would then be reduced to .6 milliamperes, as opposed to the desired drug delivery current of 2 milliamperes selected to be

applied by the adjustable current regulator circuit at the average expected skin impedance (i.e., 15,000 ohms).

Alternatively, if a DC-DC converter 24 is selected which is not self-limiting, an external zener diode D2 may be used and situated effectively in parallel with the patch/patient circuit 23. As shown in Figure 2, the zener diode D2 is connected with its cathode coupled to the output of the DC-DC converter 24 and the first electrode 6, and with its anode coupled between the output of the buffer amplifier 28 and the voltage control input of the DC-DC converter 24. A 30 volt (or other value) zener diode D1 may be selected to ensure that the voltage drop V_p across the patch/patient circuit 23 does not exceed a predetermined safe value. Thus, the controller circuit 20 provides a regulated voltage to the transdermal patch 2, which voltage is limited to prevent undesirable irritation or burns to the patient.

The controller circuit 20 will also self-regulate to apply to the patch 2 only the voltage necessary at the desired iontophoretic current should the impedance of the patient (or patch) suddenly decrease. Returning to the example given above, should the impedance of the patch/patient circuit 23 suddenly decrease from 15,000 ohms to 10,000 ohms, the voltage drop V_p across the patch would now only be 20 volts. The controller circuit is designed to react to sudden changes such that the 10 volt difference between the output voltage of the DC-DC converter 24 and the 20 volt drop across the patch will immediately be dropped across the adjustable current regulator circuit 26. Since, steady-state, this is wasteful and not energy efficient, the DC-DC converter 24 will sense the voltage at the cathode 8 of the transdermal patch and readjust the output voltage V_2 of the converter to a lower value, for example, to effect a voltage drop V_p of 20 volts across the patch electrodes

6,8, i.e., the lowest voltage necessary to conduct iontophoresis with the desired drug delivery current flow, and to minimize the voltage drop V_s across the current regulator circuit 26 in order to reduce power consumption and heat generation and to prolong the life of the battery supplying voltage V_1 . Thus, the controller circuit of the present invention not only reacts to sudden changes in the impedance of the patient (and patch), but also is self-regulating to prevent skin irritation and burns and to reduce power consumption.

Figure 3 is a detailed schematic of a preferred form of a controller circuit 20 constructed in accordance with the present invention. The adjustable current regulator circuit 26 is shown as a series pass regulator comprising MOSFET transistor Q2, resistors R3-R5, capacitor C4 and operational amplifier U2.

More specifically, voltage V_r , for adjusting the controlled current flowing through the patch, is provided to the non-inverting input of operational amplifier U2. The output of amplifier U2 is provided through resistor R3 to the gate of transistor Q2. The drain of transistor Q2 is connected to resistor R5, whose other end is grounded, and is also connected, through resistor R4, to the inverting input of amplifier U2. Capacitor C4 may be provided between the output and inverting input of amplifier U2 to eliminate oscillations.

The current regulator circuit 26 operates as any conventional series pass regulator as is well known in the art. Amplifier U2 biases transistor Q2 on to control the current flowing through transistor Q2 and resistor R5 to that which is required to make the voltage drop across resistor R5 and provided to the inverting input of amplifier U2 equal to the voltage V_r applied to the control input of the current regulator circuit, i.e., the

non-inverting input of amplifier U2. Thus, the voltage V_r applied to the circuit 26 will control the current flowing through transistor Q2. That current is the desired drug delivery current which will flow through the electrodes 6,8 of the transdermal patch 2 and through the patient's skin 10. As is well known, the current regulator circuit 26 shown in Figure 3 is self-regulating and will maintain a constant current proportional to the voltage V_r applied to the circuit. As can be seen, the source of transistor Q2 is connected to the cathode 8 of the transdermal patch 2.

The preferred DC-DC converter circuit 24 includes a step-up switching regulator integrated circuit U1, such as Part No. MAX641 manufactured by Maxim Integrated Products of Sunnyvale, California. It is envisioned, of course, that other integrated circuits may be suitable for use, or a comparable DC-DC converter may be built using discrete components.

The step-up DC-DC converter 24 uses an external inductor L1 to store energy. An oscillator internal to the MAX641 integrated circuit U1 drives the gate of a MOSFET transistor Q1 from the EXT output of the integrated circuit, which switches the MOSFET transistor Q1 on and off. The drain of the transistor Q1 is coupled to one end of the inductor L1, the other end being provided with the battery voltage V_1 . The source of transistor Q1 is connected to ground. When the transistor Q1 is turned on, current flows through the inductor L1. The current increases linearly, storing energy in the inductor L1. When the EXT output switches transistor Q1 off, the inductor's magnetic field collapses, and the voltage across the inductor reverses polarity.

A diode D1, having its anode connected to the transistor side of the inductor L1 and its cathode connected to the anode 6 of the transdermal patch, is forward biased when the voltage at the diode's anode rises to a predetermined level, delivering power to the transdermal patch. A filter capacitor C3, coupled between the cathode of diode D1 and ground, filters the output voltage ripple.

If desired, the DC-DC converter circuit 24 may include an additional MOSFET transistor Q3 connected in series with diode D1 and biased on and off by connecting its gate to a tap of inductor L1. Transistor Q3 is provided to decrease leakage current through diode D1.

Not only does transistor Q3 reduce leakage current, but it also makes the DC-DC converter circuit of the present invention at least partially failsafe to prevent continued current flow to the patch should the step-up switching regulator integrated circuit U1 fail.

More specifically, the MAX641 integrated circuit U1 includes an internal oscillator which drives transistor Q1 on and off, as mentioned previously. If the oscillator output signal fails in the high state, transistor Q1 will saturate so that the source of transistor Q3 will be substantially at ground potential (i.e., the voltage drop across saturated transistor Q1). Transistor Q3, as well as diode D1, will be non-conducting, and no current will flow from the battery (providing voltage V1) to the patch.

However, if the oscillator internal to integrated circuit U1 failed such that the signal provided to the gate of transistor Q1 is in the low state, transistor Q1 will be cut off. Without transistor Q3, current could flow from the battery through inductor L1 and diode D1

(which is in a conducting state), and to the transdermal patch electrodes 6, 8 and patient.

5 Transistor Q3, however, because it is driven by the signal from the tap of inductor L1, turns on only during the collapse of the field generated by the inductor, i.e., only during a condition of flyback in the inductor. At all other times, including during storage of energy in inductor L1, transistor Q3 is non-conducting. Accordingly, should the step-up regulator integrated
10 circuit U1 fail such that it biases transistor Q1 off, transistor Q3 will be turned off, and it will not allow current to flow from the battery through inductor L1 to the patch and patient.

15 When the output voltage V2 from the DC-DC converter 24 provided to the transdermal patch 2 reaches the desired level (for example, 30 volts), a comparator internal to the MAX641 integrated circuit U1 inhibits the signal on the EXT output, which turns off transistor Q1 to prevent further energy from being stored in the
20 inductor L1 until the patch/patient circuit 23 discharges the output filter capacitor C3 to less than the desired output voltage level.

25 The MAX641 integrated circuit U1 provides an adjustable output voltage V2 which is controlled by forming a voltage divider using series interconnected resistors R1 and R2. Resistor R1 has one end connected to ground and another end connected to resistor R2, whose other end is connected to the cathode 8 of the transdermal patch 2 and the series current regulator 26.
30 The VFB input of the MAX641 integrated circuit U1 is connected to the connection point between resistors R1 and R2. In this way, the voltage on the cathode 8 of the transdermal patch will be monitored and used to adjust the output voltage V2 of the DC-DC converter 24 provided

to the patch and across the current regulator circuit 26. An optional 100 picofarad capacitor C2 may be connected between the cathode of diode D1 and the VFB input of the MAX641 integrated circuit U1 to prevent oscillations.

5 A zener diode D2 is also provided to prevent an over-voltage condition. Diode D2 has its cathode connected to the cathode of diode D1, and its anode connected to the VFB input of the MAX641 integrated circuit. The diode D2 will conduct in its breakdown
10 region when the voltage drop V_p across the patch/patient circuit 23 exceeds a predetermined voltage. When zener diode D2 conducts, the VFB input of integrated circuit U1 will rise in voltage, turning off transistor Q1 and preventing further energy from being stored in inductor
15 L1 until the output voltage V2 provided to the patch/patient circuit 23 falls below the breakdown voltage of diode D2. In effect, diode D2 will prevent the voltage drop V_p across the patch/patient circuit 23 from exceeding more than a predetermined, safe voltage.
20 Such a situation could occur if the impedance of the patch/patient circuit exceeded a predetermined value.

 During iontophoresis, should the impedance of the patch/patient circuit 23 suddenly decrease below a
25 predetermined value, then the excess voltage not dropped across the patch/patient circuit is dropped across transistor Q2 of the current regulator circuit 26. Thus, the controller circuit 20 has the capability of reacting to sudden impedance changes in the patch/patient circuit 23, such as when the patch is readjusted on the patient
30 or the patient's skin impedance changes suddenly.

 The power dissipation caused by the voltage drop across transistor Q2 is wasteful and inefficient and, accordingly, the DC-DC converter 24 readjusts itself to lower the voltage V2 provided to the patch/patient

circuit 23 to only that which is necessary for iontophoresis at the desired delivery current, thereby reducing the voltage drop across transistor Q2. The circuit does this by monitoring the voltage on the cathode 8 of the transdermal patch 2 and providing that voltage, albeit attenuated, to the VFB input of integrated circuit U1 through the resistor network formed by resistors R1 and R2. The energization of inductor L1 is controlled so that a lower voltage will now be generated by the DC-DC converter circuit 24 and provided to the electrodes 6,8 of the patch.

A parts list for the circuit shown in Figure 4 is provided in Table I below. It is envisioned that components comparable to those listed below, connected differently to that shown in Figure 4, may be suitable to practice the invention. The battery voltage V1 may be any voltage, such as about 2 volts to about 10 volts, or more preferably, about 4 volts to about 6 volts.

TABLE I

	<u>PART</u>	<u>REFERENCE DESIGNATION</u>
20	inductor 500 μ H	L1
	diode 1N914B	D1
	diode 1N4713C 30V	D2
	transistor VN2222LL	Q1, Q2, Q3
25	step-up switching regulator MAX641	U1
	operational amplifier MAX478	U2
	capacitor 1 μ F, 10V	C1
	capacitor 100pF	C2
	capacitor 1 μ F, 35V	C3
30	capacitor 470pF	C4
	resistor 261k Ω	R1
	resistor 140k Ω	R2
	resistor 1k Ω	R3, R4
	resistor 500 Ω	R5

As can be seen from the above description, the iontophoresis system of the present invention, with its self-regulating DC-DC converter circuit 24, is highly efficient in providing the necessary power for transdermal drug delivery. The controller circuit 20 is responsive to changes in the impedance of the patient's skin and patch and adjusts the voltage and current provided to the patch as necessary, not only to prevent excessive voltage which can cause irritation or burns, but also to minimize the energy required to conduct iontophoresis effectively.

Although illustrative embodiments of the present invention have been described herein with reference to accompanying drawings, it is to be understood that the invention is not limited to those precise embodiments, and that various other changes and modifications may be effected therein by one skilled in the art without departing from the scope or spirit of the invention.

WHAT IS CLAIMED IS:

1. An iontophoresis system, which comprises:
an iontophoretic drug delivery device for
placement against the skin of a patient, the drug
delivery device having at least a first electrode and at
least a second electrode; and

a control circuit for controlling the voltage
and current provided to the at least first and second
electrodes of the drug delivery device, the control
circuit including:

a DC-DC converter circuit, the DC-DC converter
circuit generating an output voltage, the output voltage
being provided to at least one of the at least first and
second electrodes; and

a current regulator circuit, the current
regulator circuit being coupled to at least the other of
the at least first and second electrodes and providing a
desired current flow through the at least first and
second electrodes and the skin of the patient;

the DC-DC current circuit being responsive to
the voltage across the at least first and second
electrodes and adjusting the output voltage in response
thereto.

2. An iontophoresis system as defined by Claim 1,
wherein the current regulator circuit is adjustable to
provide an adjustable desired current flow through the at
least first and second electrodes.

3. An iontophoresis system as defined by Claim 1,
which further comprises:

means for limiting the voltage across the at
least first and second electrodes, the voltage limiting
means sensing when the voltage across the at least first
and second electrodes exceeds a predetermined value and

limiting the voltage thereacross to a preselected voltage.

4. An iontophoresis system, which comprises:
an iontophoretic drug delivery device for
placement against the skin of a patient, the drug
delivery device including:

5 at least a first electrode;
 means for holding a medication situated in
relation to the first electrode such that the medication
held by the medication holding means is in electrical
communication with the first electrode;

10 at least a second electrode; and
 means for holding an electrolyte situated in
relation to the second electrode such that an electrolyte
held by the electrolyte holding means is in electrical
communication with the second electrode; and

15 a control circuit for controlling the voltage
and current provided to the at least first and second
electrodes of the drug delivery device, the control
circuit including:

20 a DC-DC converter circuit, the DC-DC converter
circuit generating an output voltage, the output voltage
being provided to at least one of the at least first and
second electrodes;

25 an adjustable current regulator circuit, the
adjustable current regulator circuit being coupled to at
least the other of the at least first and second
electrodes and being adjustable to provide a desired
current flow through the at least first and second
electrodes and the skin of the patient;

30 the DC-DC converter circuit being responsive to
the voltage across the at least first and second
electrodes and adjusting the output voltage in response
thereto, the output voltage being adjusted in response to
changes in the impedance of at least one of the drug
delivery device and the skin of the patient for a desired

35 current flowing through the at least first and second electrodes and the patient's skin.

5. An iontophoresis system as defined by Claim 4, wherein the control circuit further includes:

5 a buffer amplifier, the buffer amplifier being responsive to the voltage on the other of the at least first and second electrodes and generating an output signal in response thereto, the output signal being provided to the DC-DC converter circuit, the DC-DC converter circuit being responsive to the output signal from the buffer amplifier and adjusting the output
10 voltage from the DC-DC converter circuit in response thereto.

6. An iontophoresis system as defined by Claim 4, wherein the control circuit further includes:

means for limiting the voltage across the at least first and second electrodes.

7. An iontophoresis system as defined by Claim 6, wherein the voltage limiting means includes a zener diode, the zener diode sensing a voltage across the at least first and second electrodes which is greater than a
5 preselected value and limiting the voltage thereacross in response thereto.

8. A control circuit for use with an iontophoretic drug delivery device for placement against the skin of a patient, the iontophoretic drug delivery device including at least first and second electrodes, the control circuit
5 comprising:

a DC-DC converter circuit which generates an output voltage, the output voltage being provided to at least one of the first and second electrodes; and

10 an adjustable current regulator circuit, the adjustable current regulator circuit being coupled to the

other of the at least first and second electrodes and being adjustable to provide a desired current flow through the at least first and second electrodes and through the skin of the patient;

15 the DC-DC converter circuit being responsive to the voltage across the first and second electrodes and adjusting the output voltage in response thereto.

9. An iontophoresis system control circuit for use with an iontophoretic drug delivery device, the iontophoretic drug delivery device being placeable against the skin of a patient and having at least first
5 and second electrodes, the control circuit comprising:

 a series pass regulator circuit, the series pass regulator circuit being responsive to a control voltage and controlling a desired drug delivery current in response thereto, the desired drug delivery current
10 being flowable through the at least first and second electrodes and the skin of the patient, the series pass regulator circuit having a voltage V_s thereacross, the series pass regulator circuit being electrically coupled to the at least second electrode of the iontophoretic
15 drug delivery device;

 a step-up DC-DC converter circuit, the step-up DC-DC converter circuit being electrically coupled to the at least first electrode and generating an output voltage V_2 which is provided thereto, the impedance of at least
20 one of the iontophoretic drug delivery device and the patient's skin and the desired drug delivery current flowing therethrough resulting in a voltage drop V_p across the at least first and second electrodes, wherein the voltage V_2 is equal to the sum of the voltage V_p and
25 the voltage V_s , the DC-DC converter circuit being responsive to the voltage V_p across the at least first and second electrodes and adjusting the output voltage V_2 in response thereto so that the voltage V_s across the series pass regulator is substantially equal to the

30 minimum voltage required to allow the series pass
regulator to control the desired drug delivery current
through the at least first and second electrodes and the
patient's skin.

10. A method for providing a self-regulating
voltage and current to an iontophoretic drug delivery
device of an iontophoresis system to minimize the use of
power by the system, the iontophoretic drug delivery
5 device being placeable on the skin of a patient and
including a first electrode and a second electrode, the
method comprising the steps of:

 generating a voltage V_2 provided to the first
electrode;

10 generating a desired drug delivery current to
flow through the first and second electrodes and the skin
of a patient, the desired drug delivery current being
generated by a current regulator circuit having a voltage
drop V_s thereacross, the impedance of at least one of the
15 iontophoretic drug delivery device and the patient's skin
and the desired drug delivery current flowing
therethrough resulting in a voltage drop V_p across the
first and second electrodes, the voltage V_2 being equal
to the sum of the voltage V_p and the voltage V_s ;

20 adjusting the voltage V_2 in response to a
change in the voltage drop V_p across the first and second
electrodes so that the voltage drop V_s is maintained at a
minimum voltage level.

11. A method as defined by Claim 10, which further
comprises the step of:

 preventing the voltage V_2 from increasing above
a predetermined level.

12. An iontophoresis system control circuit for use
with an iontophoretic drug delivery device, the
iontophoretic drug delivery device being placeable

against the skin of a patient and having at least first
and second electrodes, the control circuit comprising:

a series pass regulator circuit, the series
pass regulator circuit being responsive to a control
voltage and controlling a desired drug delivery current
in response thereto, the desired drug delivery current
being flowable through the at least first and second
electrodes and the skin of the patient, the series pass
regulator circuit having a voltage V_s thereacross, the
series pass regulator circuit being electrically coupled
to the at least second electrode of the iontophoretic
drug delivery device;

a step-up DC-DC converter circuit, the step-up
DC-DC converter circuit being electrically coupled to the
at least first electrode and generating an output voltage
 V_2 which is provided thereto, the impedance of at least
one of the iontophoretic drug delivery device and the
patient's skin and the desired drug delivery current
flowing therethrough resulting in a voltage drop V_p
across the at least first and second electrodes, wherein
the voltage V_2 is equal to the sum of the voltage V_p and
the voltage V_s , the DC-DC converter circuit being
responsive to the voltage V_p across the at least first
and second electrodes and adjusting the output voltage V_2
in response thereto so that the voltage V_s across the
series pass regulator is substantially equal to the
minimum voltage required to allow the series pass
regulator to control the desired drug delivery current
through the at least first and second electrodes and the
patient's skin;

wherein the step-up DC-DC converter circuit
includes:

a step-up switching regulator circuit, the
step-up switching regulator circuit generating an output
signal;

a first switching transistor, the first
switching transistor being responsive to the output


signal of the step-up switching regulator circuit and switching between a conducting and non-conducting state in response thereto;

45 an inductor, the inductor being responsive to the state of the first switching transistor and storing energy in response thereto, the inductor having a tap and generating an output signal on the tap; and

50 a second transistor, the second transistor being coupled to the tap of the inductor and being responsive to the output signal on the tap of the inductor, and switching between a conducting and non-conducting state in response thereto, the second transistor providing at least in part the output voltage V2.

1/3

FIG-1



2/3

FIG-2

20





FIG-3



INTERNATIONAL SEARCH REPORT

International Application No
PCT/US 96/14022

A. CLASSIFICATION OF SUBJECT MATTER
IPC 6 A61N1/30

According to International Patent Classification (IPC) or to both national classification and IPC

B. FIELDS SEARCHED

Minimum documentation searched (classification system followed by classification symbols)

IPC 6 A61N

Documentation searched other than minimum documentation to the extent that such documents are included in the fields searched

Electronic data base consulted during the international search (name of data base and, where practical, search terms used)

C. DOCUMENTS CONSIDERED TO BE RELEVANT

Category *	Citation of document, with indication, where appropriate, of the relevant passages	Relevant to claim No.
X	US,A,4 116 238 (PETTIJOHN) 26 September 1978	1-3
Y	see the whole document	4-12
Y	WO,A,95 09031 (BECTON) 6 April 1995 see page 9, line 7 - line 17	4-12
A	US,A,4 997 418 (DE MARTINI) 5 March 1991 see the whole document	1-12

☐ Further documents are listed in the continuation of box C.

☒ Patent family members are listed in annex.

* Special categories of cited documents :

- "A" document defining the general state of the art which is not considered to be of particular relevance
- "E" earlier document but published on or after the international filing date
- "L" document which may throw doubts on priority claim(s) or which is cited to establish the publication date of another citation or other special reason (as specified)
- "O" document referring to an oral disclosure, use, exhibition or other means
- "P" document published prior to the international filing date but later than the priority date claimed

- "T" later document published after the international filing date or priority date and not in conflict with the application but cited to understand the principle or theory underlying the invention
- "X" document of particular relevance; the claimed invention cannot be considered novel or cannot be considered to involve an inventive step when the document is taken alone
- "Y" document of particular relevance; the claimed invention cannot be considered to involve an inventive step when the document is combined with one or more other such documents, such combination being obvious to a person skilled in the art.
- "&" document member of the same patent family

Date of the actual completion of the international search

8 January 1997

Date of mailing of the international search report

17. 01. 97

Name and mailing address of the ISA

European Patent Office, P.B. 5818 Patentlaan 2
NL - 2280 HV Rijswijk
Tel. (+ 31-70) 340-2040, Tx. 31 651 epo nl,
Fax (+ 31-70) 340-3016

Authorized officer

Lemercier, D

INTERNATIONAL SEARCH REPORT

Information on patent family members

International Application No

PCT/US 96/14022

Patent document cited in search report	Publication date	Patent family member(s)	Publication date
US-A-4116238	26-09-78	JP-A- 53024550	07-03-78
WO-A-9509031	06-04-95	AU-A- 7845494	18-04-95
US-A-4997418	05-03-91	US-A- 5195953	23-03-93

THIS PAGE BLANK (USPTO)